

For use with Security+®2.0 Garage Door Openers. All Security+®2.0 Garage Door Openers have a yellow Learn button and two yellow antennas. The features are adjustable and may be turned off or on as desired. Refer to the Feature Settings section.

## Feature Overview

### SCREEN

The screen will display the time and temperature until the menu button is pressed, and then it will display the menu options. If there is a problem with the garage door opener the screen will display the Diagnostic Code.

### LIGHT BUTTON

Press the LIGHT button to turn the garage door opener lights on or off. When the lights are turned on they will stay on until the LIGHT button is pressed again, or until the garage door opener is activated. Once the garage door opener is activated the lights will turn off after the specified period of time (the factory setting is 4-1/2 minutes). The LIGHT button will not control the lights when the door is in motion. The duration of the light timing can be adjusted by accessing the menu using the navigation buttons.

### MOTION SENSOR

The motion sensor will automatically turn on the garage door opener lights when motion is detected. The lights will come on for the set period of time, then shut off. The factory setting is on and set at 4-1/2 minutes.

### LOCK

The LOCK feature is designed to prevent activation of the garage door opener from remote controls while still allowing activation from the door control and keyless entry. This feature is useful for added peace of mind when the home is empty (i.e. vacation).

### TIMER-TO-CLOSE (TTC)

DO NOT enable TTC if operating a one-piece door. TTC is to be used ONLY with sectional doors. Factory default is set to off. TTC can be set to automatically close your garage door from the fully open position after a specified period of time (1, 5, 10 minute intervals or a custom setting up to 99 minutes). The garage door opener will beep and the lights will flash before closing the door. The screen on the door control can display the status of the TTC. TTC WILL NOT work if the garage door opener is operating by battery power or if the safety reversing sensors are misaligned. This feature is NOT intended to be the primary method of closing the door. **A keyless entry should be installed in the event of an accidental lock out when using this feature.**

### MAINTENANCE ALERT SYSTEM (MAS)

This feature assists the homeowner in ensuring the garage door opener system stays in good working condition. A maintenance alert message will display on the screen indicating the garage door opener may be in need of maintenance.

The MAS feature MUST be activated at time of installation. The factory setting is off.


## ⚠️ WARNING

To prevent possible SERIOUS INJURY or DEATH from electrocution:

- Be sure power is NOT connected BEFORE installing door control.
- Connect ONLY to 24 VOLT low voltage wires.

To prevent possible SERIOUS INJURY or DEATH from a closing garage door:

- Install door control within sight of garage door, out of reach of children at a minimum height of 5 feet (1.5 m), and away from ALL moving parts of door.
- NEVER permit children to operate or play with door control push buttons or remote control transmitters.
- Activate door ONLY when it can be seen clearly, is properly adjusted, and there are no obstructions to door travel.
- ALWAYS keep garage door in sight until completely closed. NEVER permit anyone to cross path of closing garage door.




# Installation

Install the door control within sight of the door at a minimum height of 5 feet (1.5 m) where small children cannot reach, and away from the moving parts of the door. For gang box installations it is not necessary to drill holes or install the drywall anchors. Use the existing holes in the gang box.


**NOTE:** Pre-wiring means that your garage already has wires installed for the door control.

## HARDWARE




## WIRE THE DOOR CONTROL


- 1 Unplug the garage door opener to prevent the garage door opener from activating during wiring.



- 2 Strip 7/16 inch (11 mm) of insulation from one end of the wire and separate the wires.




- 3 Connect one wire to each of the two screws on the back of the door control. The wires can be connected to either screw.



**PRE-WIRED INSTALLATIONS:** Choose any two wires to connect, but make note of which wires are used.


## MOUNT THE DOOR CONTROL

- 1 Mark the location of the bottom mounting hole and drill a 5/32 inch (4 mm) hole.
- 2 Install the bottom screw, allowing 1/8 inch (3 mm) to protrude from the wall.
- 3 Position the bottom hole of the door control over the screw and slide down into place.




## WIRE TO GARAGE DOOR OPENER

- 1 Strip 7/16 inch (11 mm) of insulation from the end of the wire near the garage door opener.



- 2 Connect the wire to the red and white terminals on the garage door opener. The wires can be connected to either terminal.



**PRE-WIRED INSTALLATIONS:** Connect the same wires to the garage door opener that were previously connected to the door control.

- 3 Reconnect power to the garage door opener. If the door control has been installed and wired correctly, a message will display on the screen. To synchronize the garage door opener and the door control, press the push bar up to 3 times, until the garage door opener activates. The time and temperature will display on the door control when the door control and the garage door opener are synchronized.

# Operation

## PUSH BAR

Press the push bar to open or close the door.

## NAVIGATION BUTTONS

Use the navigation buttons to make selections and program features.

## GARAGE DOOR OPENER LIGHTS

Press the LIGHT button to turn the garage door opener lights on or off. When the lights are turned on they will stay on until the LIGHT button is pressed again, or until the garage door opener is activated. Once the garage door opener is activated the lights will turn off after the specified period of time (the factory setting is 4-1/2 minutes). The LIGHT button will not control the lights when the door is in motion.

## MOTION SENSOR

This feature will automatically turn on the garage door opener lights when motion is sensed. The lights will come on for the set period of time, then shut off.

## LIGHT FEATURE


The lights will turn on when someone enters through the open garage door and the safety reversing sensor infrared beam is broken. If using the garage door opener light as a work light, turn the light on using the light button on the wall control or the light will turn off if you are beyond the range of the sensor.

## TIMER-TO-CLOSE (TTC)


DO NOT enable TTC if operating a one-piece door. TTC is to be used ONLY with sectional doors.

Once the TTC has been set and the door is open, the selected close interval will be displayed on the screen and toggle between the time and TTC message. The garage door opener will beep and the lights will flash before closing the door.


When the TTC is on the following message will display on the door control:



To temporarily suspend the TTC feature press and release the HOLD button. Press REL button to resume normal TTC operation.




The TTC feature will deactivate if the garage door encounters an obstruction twice; or the safety reversing sensors are incorrectly installed. The garage door will reverse open and WILL NOT close until the obstructions are clear or the safety reversing sensors are correctly installed. When the obstruction has been cleared or the safety reversing sensors have been aligned, the door will close when the garage door opener is activated.





## LOCK

When the Lock feature is on, your remote controls have been disabled and the following message will display on the door control:





## BATTERY BACKUP ONLY

If your garage door opener has a battery backup one of the following messages will display on the door control if there is a problem with the battery:



## MAINTENANCE ALERT (MAS)

When the maintenance alert is on and the garage door opener needs maintenance the following message will display on the screen:




# Program

## TO ADD, REPROGRAM, OR CHANGE A REMOTE CONTROL/KEYLESS ENTRY PIN

- 1 Press the navigation button below "MENU" to view the Features menu.




- 2 Use the navigation buttons to scroll to "PROGRAM" and press the navigation button under to continue.



- 3 Select "REMOTE" or "KEYPAD" to program from the program menu. Press to continue.



- 4a Press the button on the remote control that you wish to operate your garage door.



- 4b Enter a 4-digit personal identification number (PIN) of your choice on the keyless entry keypad. Then press the ENTER button.

OR

? ? ? ?  
PIN



The garage door opener lights will flash (or two clicks will be heard) when the code has been programmed.

Repeat the steps above for programming additional remote controls or keyless entry devices. If programming is unsuccessful, refer to the remote control instructions.


# Program

## MENU NAVIGATION

The features on the door control can be programmed through a series of menus on the screen and the navigation buttons. Refer to the descriptions below.

### SCREEN

The main screen displays the time, temperature, and current battery charge (if applicable).



Navigation Buttons

### FEATURES

Press the navigation button below "MENU" to view the Features menu.



**CLOCK SETUP:** Set the time, choose 12 or 24 hour clock and show/hide clock.

**TTC SETTINGS:** Set the Timer-to-Close feature off/on and set the time interval before door closes. **NOTE: DO NOT enable TTC if operating a one-piece door. TTC is to be used ONLY with sectional doors.**

**LOCK:** Enable/disable lock.

**PROGRAM:** Add remote controls, MyQ™ devices, an extra remote button to control your garage door opener lights, or a keyless entry.

### SETTINGS

Press the navigation button below the down arrow till you see TEMPERATURE to view the Settings menu.



**TEMPERATURE:** Display the temperature in Fahrenheit or Celsius and show/hide the temperature.


**LANGUAGE:** Select a language.

**LIGHT SETTINGS:** Set duration for garage door opener light to stay on after operation, selectable range of 1-1/2 to 4-1/2 minutes. Turn the Motion sensor off/on, and turn the entry light feature off/on.

**CONTRAST:** Adjust the contrast of the screen.

### SERVICE

Press and hold the LIGHT button, then press the second navigation button to view the Service menu.



**SOFTWARE REVISION:** Displays software version information.

**CYCLE COUNT ON/OFF:** Turn the Maintenance Alert (MAS) on/off.

**TRANSMITTERS:** Displays the number of remote controls, MyQ™ devices, door controls and keyless entries currently programmed to operate the garage door opener.

**DISPLAY ERROR:** Displays any errors that have occurred.

# Warranty

## ONE YEAR LIMITED WARRANTY

The Chamberlain Group, Inc. warrants to the first consumer purchaser of this product that is free from defect in materials and/or workmanship for a period of 1 year from the date of purchase.

### DEK CANADA INC

1928 ST-REGIS BLVD.  
DORVAL, QC  
H9P 1H6

TEL: 514-685-5800  
TOLL-FREE: 1-800-361-3198  
FAX: 514-685-5804

[www.dekcanada.com](http://www.dekcanada.com)

WHEN ORDERING REPAIR PARTS  
PLEASE SUPPLY THE FOLLOWING INFORMATION:

PART NUMBER   DESCRIPTION   MODEL NUMBER